

SoftPlan Technical Bulletin

Last Updated: February 28, 1999.

Problem: Plotting to an Oce™ 9800 series plotter ignores the SoftPlan pen settings.

Users Effected: Users plotting to an Oce™ 9800 model plotter

To Fix: You must install the Windows Printing Solutions version 2.2 from Oce™ on your machine. It is available for download at http://www.oceusa.com/main/product_group.jsp
If you have any difficulties downloading or installing this application please contact (or have your plotting service) contact Oce™ technical support directly.

Install the printer driver as per the instructions from Oce™, then:

1. Select Start from the taskbar.
2. Select Settings.
3. Select Printers.
4. Select Oce™ 9800.
5. From the menu select Printer.
6. Select Properties.
7. Select the 32-bit SuperDriver Setup tab.
8. Select the Options tab.
9. Uncheck Enable HP-GL/2.
10. Select OK.
11. Select the Details tab.
12. Select Spool Settings.
13. Set the Spool data format to SMF.
14. Select OK.

Once the driver is installed and the plotter is setup correctly set your pen assignments and thickness within SoftPlan. See the SoftPlan manuals if you require assistance.

Comment: This solution may also work for the Oce™ 9400, 9500, and 9700 model plotters as they use the same printer driver.

If the problem persists, please contact SoftPlan Technical Support at:
fax:(519) 886-6955 or e-mail: support@softplantech.com.